

Here is a dimmer list that we have done. Normally we see that Eltaco works OK but we didn't have one for this test. Even if it says flicker this was only in specific areas for most of them.

| Type                         | Power | No of modules | Brand     | Model           | Max W | Min W | Min % | Flicker (perceived) | Noise | Comments                             |
|------------------------------|-------|---------------|-----------|-----------------|-------|-------|-------|---------------------|-------|--------------------------------------|
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Elko      | 400GLI          | 10,10 | 1,00  | 10%   | Yes                 | No    | Flicker                              |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Niko      | 310-0190X       | 9,90  | 0,40  | 4%    | No                  | No    |                                      |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Vadsbo    | VD200           | 8,80  | 0,60  | 7%    | Yes                 | No    | Flicker                              |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Qlight    | Monodim 350     | 9,20  | 1,20  | 25%   | Yes                 | No    | Flicker                              |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Schneider | SBD315RC        | 9,30  | 0,90  | 10%   | Yes                 | No    | Flicker                              |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | SG        | 820320 LEDIM400 | 9,10  | 0,50  | 5%    | Yes                 | No    | Flicker                              |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Elko      | 315 GLE         | 9,10  | 0,90  | 10%   | No                  | No    |                                      |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Gira      | 2262 00 / i01   | 9,20  | 2,30  | 25%   | No                  | No    | not low enough dimming               |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Q-light   | Duo touchdim    | 8,80  | 0,50  | 6%    | Yes                 | No    | Flicker                              |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Q-light   | Zerodim 350     | 9,30  | 0,80  | 9%    | No                  | No    |                                      |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Ehmann    | T14.03.1        | 8,80  | 1,50  | 17%   | No                  | No    | Not low enough dimming               |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Vadsbo    | VD300           | 6,20  | 4,00  | 65%   | Yes                 | No    | Flicker not low enough dimming range |
| Clara AC.10.230.31.927-NN.FF | 10W   | 1             | Gelia     | EF700DC         | 9,30  | 2,20  | 24%   | No                  | No    | not low enough dimming               |